

# CHAMPION

CENTURION II | 13 HP RECIPROCATING COMPRESSOR

## Compressor/Generator

### Performance & Value

Champion combined our already legendary Centurion II Compressor with the industry leading 13 HP Honda GX390 Engine and 4000-Watt Generator to continue our legacy of providing total compressed air solutions, giving you the flexibility of running both your pneumatic and electric tools off of one package.

### RV-15 Pump

Loaded with rugged features, this RV-Series 100% cast iron splash-lubricated pump utilizes special alloy steel reed valves to provide a self-cleaning design. The industrial-grade dependability of the RV-15 pump makes it possible to deliver long-lasting performance and tremendous value.

### Honda GX390 Engine

The Honda GX390 Series OHV commercial-grade engine is designed for the most demanding applications. It has set an industry standard for reliability and durability. Overhead valve design offers cooler, fuel-efficient operation and cast iron cylinder sleeve provides longer service life. The GX390 is reliable, easy starting and quiet running. Meets EPA and CARB emission levels standards.

### Electric Generator

Brushless alternator, 4000-Watt generator with (2) 120V, 15A and (1) 240V, 20A receptacles. Total harmonic distortion (THD) less than 5%, 100% copper windings.



## COMPRESSOR/GENERATOR

COMP/GEN MODEL	COMP/GEN PART NUMBER	ENGINE MODEL	GAS					HGRV7-LPH-G DIMENSIONS			APPROX. WEIGHT LBS.	175 PSI RATING		
			ENGINE HP	PUMP MODEL	CONTINUOUS GENERATOR WITH COMP OFF-LOAD	MAX GENERATOR AC OUTPUT	TANK CAP (GAL.)	L	W	H		RPM	CFM DISPL.	CFM DEL'Y
HGRV7-LPH-G	CC1153480	HONDA GX390	13	RV15A	3500-Watts	4000-Watts	(2) 4	46	22	35	490	784	22.9	17.9

### Compressor/Generator Standard Features

- Two-Stage Splash Lubricated RV15A Compressor Pump
- Honda GX390 Engine with Electric Start
- Industrial 4000-Watt Generator with (2) 120V, 15 Amp and (1) 240V, 20 Amp Receptacles
- Twin 4 Gallon Horizontal Air Receiver Tanks
  - Manual Receiver Drain Valve
- Lifting Hook
- Belt Drive with Totally Enclosed Belt Guard
- Gas Pilot Valve
- Comprehensive Base Plate Includes the Following:
  - (2) Pressure Gauges - The Left Gauge Indicates Tank Pressure, The Right Gauge Indicates Output Pressure
  - Adjustable Pressure Regulator
  - Pressure Relief Valve
  - Air Socket

### RV15 Pump

- 100% Cast Iron Pump
- Stainless Steel Reed Valves
- Large, Cast Iron Flywheel
- Industrial Grade Intake Filter and Silencer
- Deep Finned Intercooler

### Honda GX390 Engine

- 13 HP Gas Engine
- Electric Start
- OHV (Overhead Valve) Commercial Duty
- 389cc Engine Displacement

### Electric Generator

- 4000-Watt Generator
- Brushless Alternator
- Total Harmonic Distortion (THD) less than 5%
- 100% Copper Windings

**CHAMPION®**

1301 North Euclid Avenue  
Princeton, Illinois 61356 USA  
866-276-4330  
[www.ChampionPneumatic.com](http://www.ChampionPneumatic.com)



©2016 Gardner Denver, Inc. Printed in U.S.A.  
CRCS-RV15A-CG 1st Ed. 5/16